

IRISH RAILWAY DCC SOUNDS

Irish 001 'A' Class Crossley Engine Function List

F Key	Description	Feature
F0	Side lights/tail lights	Directional
F1	Sound ON/OFF with hand brake.	Oil pump CV155
F2	Horn	Short
F3	Horn	Payable
F4	Buffer clash⌘/coupling*	
F5	Brakes normal	CV179 adjusts braking intensity
F6	Brakes Emergency	CV180 adjusts braking intensity
F7	Blower⌘	Latching
F8	Head Light	Directional
F9	Curve squeal⌘	Latching
F10	Guards whistle*	
F11	Wagon buffer clash⌘	
F12	Radio call	
F13	Station announcement*	CV168= 0-8 Changes station name
F14	Sanding valve	Latching
F15	Automatic uncoupling shuffle	
F16	Radiator fan	Latching
F17	Shunting mode	Default Light Load/ON Light Engine, shunting lights
F18	Heavy mode	Heavy Load over rides F17 if on
F19	Volume control	Scroll through volumes
F20	Train Mode	Turns OFF RedTail Lights
F21	Parking Mode	Turns ON All Red side lights, turns OFF all others
F22	Compressor	Latching
F23	Cab lights*	
F24	Not used	
F25	Engine room lights	
F26	Not used	
F27	Not used	
F28	Not used	

* Does not work when loco is moving.

⌘ Only works when loco is moving.

Latching means that the sound will come on when the F key is pressed and continue until the F key is pressed again.

Oil pump CV155=0 OFF, CV155=1 short cycle(default), CV155=2 Full recording from prototype